



**CEX-6 COMMON EXCITER**



**CEX-11 / 16 / 21**

**MECHANICAL**

Height (CEX-6)	1.750"
Height (CX-11)	3.500"
Height (CX-16)	5.250"
Height (CX-21)	7.000"
Width	17.250"
Depth	10.500"

**APPLICATIONS**

- Multi-Stage Semiconductor Manufacturing
- Multi-Stage Plasma Coaters (Web, Metals, quartz, Etc)
- LCD Multi-Stage Coaters
- Multi-Stage Glass Coaters
- Multi-Stage Solar Panel Coaters

**CEX-6 COMMON EXCITER**

- Our common exciter controls 1-6 RF generator's signals
- Lightweight chassis @ 3 lbs
- Phase shift capabilities range from 0-180 and 180-360 degrees
- 19" rack mount
- Frequency stability 0.05%
- BMC type connectors used for easy set-up
- Compatible with all models RF generators
- Air cooled
- 100-240 vac variable AC input
- Independent shut off mode for each channel
- Multi-ganged models available (see above)

